

ZerOS Software Release (Public Release)

| | | | |
|-------------------|---------|---------------|-----------------------------|
| Released Version: | 7.8.3 | Release Date: | 22 nd June 2015 |
| Previous Version | 7.8.2.7 | Release Date: | 31 st March 2015 |

ZerOS 7.8.3 Software Release

Introduction

Release 7.8.3 of ZerOS is a minor new software release recommended for all FLX lighting consoles. These release notes describe the new features and bug fixes that have been implemented between versions 7.8.2.7 and 7.8.3.

This software will not install on any other ZerOS console apart from FLX.

Products Affected

✓ FLX

Compatibility

No compatibility issues known from 7.8.2.7.

FLX show files will not currently load onto other ZerOS consoles. Show files from other ZerOS consoles will load successfully onto FLX.

Update Instructions

Please familiarize yourself with these update instructions before proceeding. Instructions must be followed accurately and in order. Deviations or omissions could render the desk unusable and require it to be returned to the factory for recovery.

If any difficulties are encountered at any point, or you are in doubt on any of the instructions below, then do not proceed any further with the update and contact Zero 88 for assistance.

The software installation process completely removes all data on the console, including any current show files. If the current show file is still required, **please ensure that backups are taken before proceeding with the update**. After completing the update you may re-load your show if required.

When performing a software update it is important to ensure that the power supply to your desk is stable and reliable. Power loss during a software update can render your desk unusable.

To perform the update:

- Download the software from the Zero 88 website (zero88.com/software/zeros)
- Unzip the download and save the .exe file onto a USB stick (don't put it inside any folders)
- Plug the USB stick into your console
- Press SETUP to enter the console's setup screen and choose "Load file" on the monitor
- Select the file from the list displayed on screen and follow the onscreen instructions
- Once the update is complete, remove the USB Memory Stick and reboot the desk

Once all the software is up to date, you can get on with enjoying the new features in the desk software. Zero 88 recommend printing these Release Notes and having them with you when operating the desk, as some functionality may have changed which is explained in these notes.

Enhancements and Bug Fixes

| | |
|-----------------|--|
| ZOS-5739 | Additional monitor resolutions now supported |
| ZOS-5744 | Added support for ZerOS Wing |
| ZOS-5755 | LEDs no longer flash once delete syntax is complete |
| ZOS-5871 | Hue & Saturation values are no longer lost when Value is reduced to 0 |
| ZOS-5929 | Drop down menus now display correctly within their window |
| ZOS-5934 | All windows and popups now fill the whole of the internal touchscreen |
| ZOS-5950 | Scroll Bars are now wider, scroll faster, and stop where you touch in the scroll bar area |
| ZOS-6055 | Logo updated for all ZerOS applications |
| ZOS-6085 | ZerOS for FLX made independent from the rest of ZerOS and Phantom ZerOS (temporarily) |
| ZOS-6099 | Record Window can now be accessed by pressing and holding RECORD. Display options available within Setup. |
| ZOS-6111 | Default desk name now correctly updated after serial number is retrieved from co-processor. |
| ZOS-6115 | When recording in tracking mode, the programmer will now only clear if the playback fader is above the “trigger level” |
| ZOS-6129 | RGB fixtures now displayed correctly in the Output Window when the “Default” is changed within SETUP |
| ZOS-6139 | Issue fixed when closing the “Input Capture” window |
| ZOS-6140 | New tracking options – Off, Basic, Advanced |
| ZOS-6147 | Deselecting channels on the MFFs after pressing an attribute key is now valid syntax |
| ZOS-6148 | Keyboard now appears full screen on the internal touchscreen |
| ZOS-6149 | Playback window on touch screen now condensed to display correctly |
| ZOS-6150 | SETUP+GO after an attribute key is now valid syntax |
| ZOS-6152 | Fixed issue when pressing Shift-UDK |
| ZOS-6156 | If external monitor isn’t used, the Command Line’s displayed internally and the Output Window can be viewed using SHIFT+VIEW |
| ZOS-6157 | Debug files now ensure the watchdog can’t overwrite the crash data from the exception handler |
| ZOS-6170 | When enabled, the Error Tone no longer sounds on “GO” press |
| ZOS-6187 | Smart Phone Remote App User Interface update and improved |
| ZOS-6211 | The “selected” cell code has been improved, solving issues with UPDATE ENTER and the “Waveforms” tab of the Effects Window |
| ZOS-6215 | Issue fixed where the “Network Devices” window could crash console |
| ZOS-6224 | “Stage Sizing” temporarily disabled |
| ZOS-6236 | “Random” button in Mood Boards temporarily disabled |
| ZOS-6254 | New “resolution” option for the external monitor available in SETUP > System Settings > External Display Settings |
| ZOS-6265 | ENTER ENTER syntax no longer causes beep if error tone is enabled |
| ZOS-6266 | Changing “function” in Waveforms Effect Tab no longer causes beep if error tone is enabled |
| ZOS-6267 | ENTER key now works correctly when within the Patch Screen |
| ZOS-6268 | Issue fixed which could cause console to crash |
| ZOS-6270 | When updating a cue in the Master Playback, the cue is now automatically replayed and the programmer automatically cleared |
| ZOS-6284 | SHIFT+UDK functionality wasn’t working as expected |
| ZOS-6285 | “Trigger” options within Cue Settings window updated to reflect correct FLX functionality |
| ZOS-6286 | “Timecode Mode” options within Stack Settings window updated to reflect correct FLX functionality |
| ZOS-6287 | “Recovery Mode” option now working correctly |
| ZOS-6289 | “Clear Options” within SETUP updated to reflect correct FLX functionality |
| ZOS-6297 | Fixture Library 29 now included within ZerOS |
| ZOS-6298 | Art-Net port and universe settings now store correctly when leaving SETUP |
| ZOS-6321 | “Change Pin” option added within the “Z” button menu |
| ZOS-6328 | Attribute palettes can now only store parameters from within that attribute |

Known Issues

No known issues.